### DW-MAX Backup Locally to USB

----



) Click BAC	JK-UP	
	MAIN MENU	
DISPLAY S RECORD CONFIGUR EXTER ALL BACK-UP FIRMWARE FACTORY	ETUP ATION DEVICE UPGRADE DEFAULT	
LANGUAGE	Ξ	ENGLISH
		EXIT



If you need technical assistant please Call:866-446-3516 option#2

# **DW-MAX Backup Remotely**

(2) Select a Site and click **OK** 

(1) Launch the software and click NETWORK SETUP



#### (4) Click on BACKUP



All All and a state of the						×
SITE SETUP						1
ADDRESS	LOCATION	PORT #	TYPE	D	REGISTERING SITE	P
192.168.250.58	Digital	12555	1P	imin _		
					UPDATE	
				F		
					DELETE	
				-	- Aur	
					AVE	
					OK.	
					-	
					CANCE	
0					CHURCLE	

## (5) Click on Connect Test

	BACKUP		Ver 1. 0. 0. 7
Backup Informati		OVR Server Info	ormation
■ IP Address 192.168.250.58	Recorded S	art Time	
Network Port 12555	Recorded E	nd Time	
User ID admin			Update
User Password			
Save File Path		Backup St	atus
Start Backup Time	00 Message		
End Backup Tim	00 Receive Rate		
	Backup Rate	s	
	Receive bps		
Connect Test Lo	Save Size		
Set Backup Time Start B	laekup		
			Close

#### (3) Enter the password and click LOGIN



#### (6) If you see "Success Connect Test!", click on Lock

		BACKUP	Ver 1. 0. 0. 7
Bac	kup Information		OVR Server Information
■ IP Address	192.168.250.58	Recorded St	tart Time
Network Port	12555	Recorded En	nd Tiple
User ID	admin		Update
User Password			
Save File Path			Backup Status
Start Backup Time	0000/00/00 00:00:00	Message	Sucess Connect Test !
End Backup Time	0000/00/00 00:00:00	Receive Rate	35
	· · · · · · · · · · · · · · · · · · ·	Backup Rate	S
Connect To		Receive bps	
Connect re		Save Size	
Set Backup T	ime Start Backup		
			Close

(7) Once you see "Update Record Time!", Click **Set Backup Time** 

	BACKUP	Ver 1. 0. 0. 7
Backu		DVR Server Information
IP Address 22.168.250.58	Recorded St	tart Time 2009/04/14 13:12:11
Network Port	Recorded E	nd Time 2009/04/17 14:54:18
User ID admin		Update
User Password		
Save File Path		Backup Status
Start Backup T ne 0000/00/00 00:00:00	Message	Update Record Time !
End Backup I ma 0000/00/00 00:00:00	Receive Rate	es
	Backup Rate	15
	Receive bps	3
Set Backup Time Start Backup	Save Size	

(10) You can click **Stop Backup** whenever or wait until the backup is complete

B	BACI UP Ver 1. 0. 0. 7
Backup Information	DVR Server Information
IP Address         192.168.250.58           Network Port         1/2555           User ID         admin	Recorded Start Time 2009/04/1413:12:11     Recorded End Time 2009/04/1715:19:36     Update
User Password Save File Path C:\Documents and Settings\techs	Backup Status
Start Backup Time         2009/04/14 13:13:00           End Backup Time         2009/04/17 15:07:07	Message Complete Receive Image I     Receive Rates     Backup Rates
Connect Test Unlock Set Backup Time Stop Backup	Receive bps 321536 bytes     Save Size S Mbytes
	Close

## DW-MAX Backup Remotely (cont.)

(8) Click **Find** and set the destination of the file. Set the File Size, also the Start and End Backup Time and click **Apply** 



(11) Go to the destination of the file, you should see your backup



(9) Once your Start and End Backup are updated click **Start Backup** 

B	ACKUP	Ver 1. 0. 0. 7
Back, p Information		VR Server Information
IP Address         13, 168, 250, 58           Network Port         123,	<ul> <li>Recorded St</li> <li>Recorded Er</li> </ul>	art Time 2009/04/14 13:12:11 nd Time 2009/04/17 15:07:16
User ID admin		Update Backup Status
Start Backup Time 2009/04/14 312:11 End Backup Time 2009/04/17 1: 07:07	Message     Receive Rate     Backup Rate	Update Record Time I
Connect Test Unick Set Backup Time Start Backup	Receive bps     Save Size	Cinco

If you need technical assistant please Call:866-446-3516 option#2